Function command summary table:

Model Name >>			S1210 S1212 S1213	X1140 X1140A X1240	H6510BD	P1340W X1340WH P1341W P1340WG P1500	S1213Hne S1213Hn	P5207B P5307WB	X1173 X1173A X1273
Supported baud rates		110	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		300	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		600	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		1200	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		2400	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		4800	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		9600	support	support	support	support	support	support	support
		14400	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		19200	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		38400	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		57600	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		115200	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
No	Code (character)	Function feature							
1	OKOKOKOKOK\r	Power On	support	support	support	support	support	support	support
2	* 0 IR 001\r	Power On	support	support	support	support	support	support	support
3	* 0 IR 002\r	Power Off	support	support	support	support	support	support	support
4	* 0 IR 004\r	Keystone	support	support	support	support	support	support	support

Model Name >>			S1210 S1212 S1213	X1140 X1140A X1240	H6510BD	P1340W X1340WH P1341W P1340WG P1500	S1213Hne S1213Hn	P5207B P5307WB	X1173 X1173A X1273
5	* 0 IR 006\r	Mute	support	support	support	support	support	support	support
6	* 0 IR 007\r	Freeze	support	support	support	support	support	support	support
7	* 0 IR 008\r	Menu	support	support	support	support	support	support	support
8	* 0 IR 009\r	Up	support	support	support	support	support	support	support
9	* 0 IR 010\r	Down	support	support	support	support	support	support	support
10	* 0 IR 011\r	Right	support	support	support	support	support	support	support
11	* 0 IR 012\r	Left	support	support	support	support	support	support	support
12	* 0 IR 013\r	Enter	**Unsupport**	**Unsupport**	**Unsupport**	**Unsupport**	**Unsupport**	**Unsupport**	**Unsupport**
13	* 0 IR 014\r	Re-Sync	support	support	support	support	support	support	support
14	* 0 IR 015\r	Source Analog RGB for D-sub	support	support	support	support	support	support	support
15	* 0 IR 016\r	Source Digital RGB(DVI)	**Unsupport**	**Unsupport**	**Unsupport**	**Unsupport**	**Unsupport**	**Unsupport**	**Unsupport**
16	* 0 IR 017\r	Source PbPr for D-sub	support	support	support	support	support	support	support
17	* 0 IR 018\r	Source S-Video	support	support	support	support	support	support	support
18	* 0 IR 019\r	Source Composite Video	support	support	support	support	support	support	support
19	* 0 IR 020\r	Source Component Video	**Unsupport**	**Unsupport**	support	**Unsupport**	**Unsupport**	**Unsupport**	**Unsupport**
20	* 0 IR 021\r	Aspect ratio 16:9	support	support	support	support	support	support	support
21	* 0 IR 022\r	Aspect ratio 4:3	support	support	support	support	support	support	support

Model Name >>			S1210 S1212 S1213	X1140 X1140A X1240	H6510BD	P1340W X1340WH P1341W P1340WG P1500	S1213Hne S1213Hn	P5207B P5307WB	X1173 X1173A X1273
22	* 0 IR 023\r	Volume +	support	support	support	support	support	support	support
23	* 0 IR 024\r	Volume –	support	support	support	support	support	support	support
24	* 0 IR 025\r	Brightness	support	support	support	support	support	support	support
25	* 0 IR 026\r	Contrast	support	support	support	support	support	support	support
26	* 0 IR 027\r	Color Temperature	support	support	support	support	support	support	support
27	* 0 IR 028\r	Source Analog RGB for DVI Port(DVI-A)	**Unsupport**	**Unsupport**	**Unsupport**	**Unsupport**	**Unsupport**	**Unsupport**	**Unsupport**
28	* 0 IR 029\r	Source Analog YPbPr for DVI Port	**Unsupport**	**Unsupport**	**Unsupport**	**Unsupport**	**Unsupport**	**Unsupport**	**Unsupport**
29	* 0 IR 030\r	Hide	support	support	support	support	support	support	support
30	* 0 IR 031\r	Source	support	support	support	support	support	support	support
31	* 0 IR 032\r	Video: Color saturation adjustment	support	support	support	support	support	support	support
32	* 0 IR 033\r	Video: Hue adjustment	support	support	support	support	support	support	support
33	* 0 IR 034\r	Video: Sharpness adjustment	support	support	support	support	support	support	support
34	* 0 IR 035\r	Query Model name	support	support	support	support	support	support	support
35	* 0 IR 036\r	Query Native display resolution	support	support	support	support	support	support	support
36	* 0 IR 037\r	Query company name	support	support	support	support	support	support	support
37	* 0 IR 040\r	Aspect ratioL.Box	**Unsupport**	**Unsupport**	support	support	**Unsupport**	support	**Unsupport**

Model Name >>			S1210 S1212 S1213	X1140 X1140A X1240	H6510BD	P1340W X1340WH P1341W P1340WG P1500	S1213Hne S1213Hn	P5207B P5307WB	X1173 X1173A X1273
38	* 0 IR 041\r	Aspect ratio 1:1	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
39	* 0 IR 042\r	Keystone Up	support	support	support	support	support	support	support
40	* 0 IR 043\r	Keystone Down	support	support	support	support	support	support	support
41	* 0 IR 044\r	Keystone Left	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
42	* 0 IR 045\r	Keystone Right	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
43	* 0 IR 046\r	Zoom	support	support	support	support	support	support	support
44	* 0 IR 047\r	e-Key	support	support	support	support	support	support	Unsupport
45	* 0 IR 048\r	Color RGB	support	support	support	support	support	support	support
46	* 0 IR 049\r	Language	support	support	support	support	support	support	support
47	* 0 IR 050\r	Source HDMI	Unsupport	Unsupport	support	support	support	support	Unsupport
48	* 0 IR 051\r	ECO mode	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
49	* 0 IR 052\r	Query ECO mode	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
50	* 0 Lamp ?\r	Query the lamp ON/OFF	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
51	* 0 Lamp\r	Query the lamp hours	support	support	support	support	support	support	support
52	* 0 Src ?\r	Query source input type	support	support	support	support	support	support	support

Function command summary table:

Model Name >>			P1173	X1373WH	X1160 X1160Z X1161 X1161A X1161N X110	H5350	P5370W	P7500	P7203 P7200i P7205 P7203B
Supported baud rates		110	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		300	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		600	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		1200	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		2400	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		4800	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		9600	support	support	Unsupport	Unsupport	support	support	support
		14400	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		19200	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		38400	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		57600	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		115200	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
No	Code (character)	Function feature							
1	OKOKOKOKOK\r	Power On	support	support	Unsupport	Unsupport	support	support	support
2	* 0 IR 001\r	Power On	support	support	Unsupport	Unsupport	support	support	support
3	* 0 IR 002\r	Power Off	support	support	Unsupport	Unsupport	support	support	support
4	* 0 IR 004\r	Keystone	support	support	Unsupport	Unsupport	support	support	support

Model Name >>			P1173	X1373WH	X1160 X1160Z X1161 X1161A X1161N X110	H5350	P5370W	P7500	P7203 P7200i P7205 P7203B
5	* 0 IR 006\r	Mute	support	support	Unsupport	Unsupport	support	support	support
6	* 0 IR 007\r	Freeze	support	support	Unsupport	Unsupport	support	support	support
7	* 0 IR 008\r	Menu	support	support	Unsupport	Unsupport	support	support	support
8	* 0 IR 009\r	Up	support	support	Unsupport	Unsupport	support	support	support
9	* 0 IR 010\r	Down	support	support	Unsupport	Unsupport	support	support	support
10	* 0 IR 011\r	Right	support	support	Unsupport	Unsupport	support	support	support
11	* 0 IR 012\r	Left	support	support	Unsupport	Unsupport	support	support	support
12	* 0 IR 013\r	Enter	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
13	* 0 IR 014\r	Re-Sync	support	support	Unsupport	Unsupport	support	support	support
14	* 0 IR 015\r	Source Analog RGB for D-sub	support	support	Unsupport	Unsupport	support	support	support
15	* 0 IR 016\r	Source Digital RGB(DVI)	Unsupport	Unsupport	Unsupport	Unsupport	support	support	support
16	* 0 IR 017\r	Source PbPr for D-sub	support	support	Unsupport	Unsupport	support	support	support
17	* 0 IR 018\r	Source S-Video	support	support	Unsupport	Unsupport	support	support	support
18	* 0 IR 019\r	Source Composite Video	support	support	Unsupport	Unsupport	support	support	support
19	* 0 IR 020\r	Source Component Video	Unsupport	Unsupport	Unsupport	Unsupport	support	support	support
20	* 0 IR 021\r	Aspect ratio 16:9	support	support	Unsupport	Unsupport	support	support	support
21	* 0 IR 022\r	Aspect ratio 4:3	support	support	Unsupport	Unsupport	support	support	support

Model Name >>			P1173	X1373WH	X1160 X1160Z X1161 X1161A X1161N X110	H5350	P5370W	P7500	P7203 P7200i P7205 P7203B
22	* 0 IR 023\r	Volume +	support	support	Unsupport	Unsupport	support	support	support
23	* 0 IR 024\r	Volume –	support	support	Unsupport	Unsupport	support	support	support
24	* 0 IR 025\r	Brightness	support	support	Unsupport	Unsupport	support	support	support
25	* 0 IR 026\r	Contrast	support	support	Unsupport	Unsupport	support	support	support
26	* 0 IR 027\r	Color Temperature	support	support	Unsupport	Unsupport	support	support	support
27	* 0 IR 028\r	Source Analog RGB for DVI Port(DVI-A)	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
28	* 0 IR 029\r	Source Analog YPbPr for DVI Port	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
29	* 0 IR 030\r	Hide	support	support	Unsupport	Unsupport	support	support	support
30	* 0 IR 031\r	Source	support	support	Unsupport	Unsupport	support	support	support
31	* 0 IR 032\r	Video: Color saturation adjustment	support	support	Unsupport	Unsupport	support	support	support
32	* 0 IR 033\r	Video: Hue adjustment	support	support	Unsupport	Unsupport	support	support	support
33	* 0 IR 034\r	Video: Sharpness adjustment	support	support	Unsupport	Unsupport	support	support	support
34	* 0 IR 035\r	Query Model name	support	support	Unsupport	Unsupport	support	support	support
35	* 0 IR 036\r	Query Native display resolution	support	support	Unsupport	Unsupport	support	support	support
36	* 0 IR 037\r	Query company name	support	support	Unsupport	Unsupport	support	support	support
37	* 0 IR 040\r	Aspect ratioL.Box	Unsupport	support	Unsupport	Unsupport	support	support	Unsupport

Model Name >>			P1173	X1373WH	X1160 X1160Z X1161 X1161A X1161N X110	H5350	P5370W	P7500	P7203 P7200i P7205 P7203B
38	* 0 IR 041\r	Aspect ratio 1:1	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
39	* 0 IR 042\r	Keystone Up	support	support	Unsupport	Unsupport	support	support	support
40	* 0 IR 043\r	Keystone Down	support	support	Unsupport	Unsupport	support	support	support
41	* 0 IR 044\r	Keystone Left	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	support
42	* 0 IR 045\r	Keystone Right	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	support
43	* 0 IR 046\r	Zoom	support	support	Unsupport	Unsupport	support	support	support
44	* 0 IR 047\r	e-Key	Unsupport	Unsupport	Unsupport	Unsupport	support	support	support
45	* 0 IR 048\r	Color RGB	support	support	Unsupport	Unsupport	support	support	support
46	* 0 IR 049\r	Language	support	support	Unsupport	Unsupport	support	support	support
47	* 0 IR 050\r	Source HDMI	support	support	Unsupport	Unsupport	support	support	support
48	* 0 IR 051\r	ECO mode	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
49	* 0 IR 052\r	Query ECO mode	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
50	* 0 Lamp ?\r	Query the lamp ON/OFF	Unsupport	Unsupport	Unsupport	Unsupport	support	support	support
51	* 0 Lamp\r	Query the lamp hours	support	support	Unsupport	Unsupport	support	support	support
52	* 0 Src ?\r	Query source input type	support	support	Unsupport	Unsupport	support	support	support

Function command summary table:

Model Name >>			H9500BD	H5360	P7213 P7215	X1261P	X1261PN	X1161P X1161PA X1161PN	H5360BD	K750	C120
Supported baud rates		110	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		300	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		600	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		1200	support	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		2400	support	Unsupport	support	support	Unsupport	Unsupport	support	support	Unsupport
		4800	support	Unsupport	support	support	Unsupport	Unsupport	support	support	Unsupport
		9600	support	support	support	support	Unsupport	Unsupport	support	support	Unsupport
		14400	Unsupport	Unsupport	support	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		19200	support	Unsupport	support	support	Unsupport	Unsupport	support	support	Unsupport
		38400	support	Unsupport	support	support	Unsupport	Unsupport	support	support	Unsupport
		57600	support	Unsupport	support	support	Unsupport	Unsupport	support	support	Unsupport
		115200	Unsupport	Unsupport	support	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
No	Code (character)	Function feature									
1	OKOKOKOKOK\r	Power On	support	support	support	support	Unsupport	Unsupport	support	support	Unsupport
2	* 0 IR 001\r	Power On	support	support	support	support	Unsupport	Unsupport	support	support	Unsupport
3	* 0 IR 002\r	Power Off	support	support	support	support	Unsupport	Unsupport	support	support	Unsupport
4	* 0 IR 004\r	Keystone	support	support	support	support	Unsupport	Unsupport	support	support	Unsupport

Model Name >>			H9500BD	H5360	P7213 P7215	X1261P	X1261PN	X1161P X1161PA X1161PN	H5360BD	K750	C120
5	* 0 IR 006\r	Mute	Unsupport	support	support	support	Unsupport	Unsupport	support	support	Unsupport
6	* 0 IR 007\r	Freeze	support	support	support	support	Unsupport	Unsupport	support	support	Unsupport
7	* 0 IR 008\r	Menu	support	support	support	support	Unsupport	Unsupport	support	support	Unsupport
8	* 0 IR 009\r	Up	support	support	support	support	Unsupport	Unsupport	support	support	Unsupport
9	* 0 IR 010\r	Down	support	support	support	support	Unsupport	Unsupport	support	support	Unsupport
10	* 0 IR 011\r	Right	support	support	support	support	Unsupport	Unsupport	support	support	Unsupport
11	* 0 IR 012\r	Left	support	support	support	support	Unsupport	Unsupport	support	support	Unsupport
12	* 0 IR 013\r	Enter	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
13	* 0 IR 014\r	Re-Sync	support	support	support	support	Unsupport	Unsupport	support	support	Unsupport
14	* 0 IR 015\r	Source Analog RGB for D-sub	support	support	support	support	Unsupport	Unsupport	support	support	Unsupport
15	* 0 IR 016\r	Source Digital RGB(DVI)	support	Unsupport	support	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
16	* 0 IR 017\r	Source PbPr for D-sub	support	support	support	support	Unsupport	Unsupport	support	support	Unsupport
17	* 0 IR 018\r	Source S-Video	support	support	support	support	Unsupport	Unsupport	support	support	Unsupport
18	* 0 IR 019\r	Source Composite Video	support	support	support	support	Unsupport	Unsupport	support	support	Unsupport
19	* 0 IR 020\r	Source Component Video	support	support	support	Unsupport	Unsupport	Unsupport	support	Unsupport	Unsupport
20	* 0 IR 021\r	Aspect ratio 16:9	support	support	support	support	Unsupport	Unsupport	support	support	Unsupport
21	* 0 IR 022\r	Aspect ratio 4:3	support	support	support	support	Unsupport	Unsupport	support	support	Unsupport

Model Name >>			H9500BD	H5360	P7213 P7215	X1261P	X1261PN	X1161P X1161PA X1161PN	H5360BD	K750	C120
22	* 0 IR 023\r	Volume +	Unsupport	support	support	support	Unsupport	Unsupport	support	support	Unsupport
23	* 0 IR 024\r	Volume –	Unsupport	support	support	support	Unsupport	Unsupport	support	support	Unsupport
24	* 0 IR 025\r	Brightness	support	support	support	support	Unsupport	Unsupport	support	support	Unsupport
25	* 0 IR 026\r	Contrast	support	support	support	support	Unsupport	Unsupport	support	support	Unsupport
26	* 0 IR 027\r	Color Temperature	support	support	support	support	Unsupport	Unsupport	support	support	Unsupport
27	* 0 IR 028\r	Source Analog RGB for DVI Port(DVI-A)	Unsupport	Unsupport	support	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
28	* 0 IR 029\r	Source Analog YPbPr for DVI Port	Unsupport	Unsupport	support	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
29	* 0 IR 030\r	Hide	support	support	support	support	Unsupport	Unsupport	support	support	Unsupport
30	* 0 IR 031\r	Source	support	support	support	support	Unsupport	Unsupport	support	support	Unsupport
31	* 0 IR 032\r	Video: Color saturation adjustment	support	support	support	support	Unsupport	Unsupport	support	support	Unsupport
32	* 0 IR 033\r	Video: Hue adjustment	support	support	support	support	Unsupport	Unsupport	support	support	Unsupport
33	* 0 IR 034\r	Video: Sharpness adjustment	support	support	support	support	Unsupport	Unsupport	support	support	Unsupport
34	* 0 IR 035\r	Query Model name	support	support	support	support	Unsupport	Unsupport	support	support	Unsupport
35	* 0 IR 036\r	Query Native display resolution	support	support	support	support	Unsupport	Unsupport	support	support	Unsupport
36	* 0 IR 037\r	Query company name	support	support	support	support	Unsupport	Unsupport	support	support	Unsupport
37	* 0 IR 040\r	Aspect ratioL.Box	support	support	Unsupport	Unsupport	Unsupport	Unsupport	support	support	Unsupport

Model Name >>			H9500BD	H5360	P7213 P7215	X1261P	X1261PN	X1161P X1161PA X1161PN	H5360BD	K750	C120
38	* 0 IR 041\r	Aspect ratio 1:1	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
39	* 0 IR 042\r	Keystone Up	support	support	support	support	Unsupport	Unsupport	support	support	Unsupport
40	* 0 IR 043\r	Keystone Down	support	support	support	support	Unsupport	Unsupport	support	support	Unsupport
41	* 0 IR 044\r	Keystone Left	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
42	* 0 IR 045\r	Keystone Right	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
43	* 0 IR 046\r	Zoom	support	support	support	support	Unsupport	Unsupport	support	support	Unsupport
44	* 0 IR 047\r	e-Key	support	support	support	support	Unsupport	Unsupport	support	support	Unsupport
45	* 0 IR 048\r	Color RGB	support	support	Unsupport	support	Unsupport	Unsupport	support	support	Unsupport
46	* 0 IR 049\r	Language	support	support	support	support	Unsupport	Unsupport	support	support	Unsupport
47	* 0 IR 050\r	Source HDMI	support	support	support	Unsupport	Unsupport	Unsupport	support	support	Unsupport
48	* 0 IR 051\r	ECO mode	support	Unsupport	support	support	Unsupport	Unsupport	support	support	Unsupport
49	* 0 IR 052\r	Query ECO mode	support	Unsupport	support	support	Unsupport	Unsupport	support	support	Unsupport
50	* 0 Lamp ?\r	Query the lamp ON/OFF	support	support	support	support	Unsupport	Unsupport	support	Unsupport	Unsupport
51	* 0 Lamp\r	Query the lamp hours	support	support	support	support	Unsupport	Unsupport	support	Unsupport	Unsupport
52	* 0 Src ?\r	Query source input type	support	support	support	support	Unsupport	Unsupport	support	support	Unsupport

Function command summary table:

Model Name >>			X1170	X1270	X1276	P1373W	H6500	H5370BD	X1263	P1163 P1273 P1276 P1273B	P1373WB
Supported baud rates		110	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		300	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		600	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		1200	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		2400	Unsupport	support	Unsupport	Unsupport	Unsupport	Unsupport	support	support	support
		4800	Unsupport	support	Unsupport	Unsupport	Unsupport	Unsupport	support	support	support
		9600	Unsupport	support	support	support	Unsupport	support	support	support	support
		14400	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	support	Unsupport	Unsupport	Unsupport
		19200	Unsupport	support	Unsupport	Unsupport	Unsupport	support	support	support	support
		38400	Unsupport	support	Unsupport	Unsupport	Unsupport	support	support	support	support
		57600	Unsupport	support	Unsupport	Unsupport	Unsupport	support	support	support	support
		115200	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	support	Unsupport	Unsupport	Unsupport
No	Code (character)	Function feature									
1	OKOKOKOKOK\r	Power On	Unsupport	support	support	support	Unsupport	support	support	support	support
2	* 0 IR 001\r	Power On	Unsupport	support	support	support	Unsupport	support	support	support	support
3	* 0 IR 002\r	Power Off	Unsupport	support	support	support	Unsupport	support	support	support	support
4	* 0 IR 004\r	Keystone	Unsupport	support	support	support	Unsupport	support	support	support	support

Model Name >>			X1170	X1270	X1276	P1373W	H6500	H5370BD	X1263	P1163 P1273 P1276 P1273B	P1373WB
5	* 0 IR 006\r	Mute	Unsupport	support	support	support	Unsupport	support	support	support	support
6	* 0 IR 007\r	Freeze	Unsupport	support	support	support	Unsupport	support	support	support	support
7	* 0 IR 008\r	Menu	Unsupport	support	support	support	Unsupport	support	support	support	support
8	* 0 IR 009\r	Up	Unsupport	support	support	support	Unsupport	support	support	support	support
9	* 0 IR 010\r	Down	Unsupport	support	support	support	Unsupport	support	support	support	support
10	* 0 IR 011\r	Right	Unsupport	support	support	support	Unsupport	support	support	support	support
11	* 0 IR 012\r	Left	Unsupport	support	support	support	Unsupport	support	support	support	support
12	* 0 IR 013\r	Enter	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
13	* 0 IR 014\r	Re-Sync	Unsupport	support	support	support	Unsupport	support	support	support	support
14	* 0 IR 015\r	Source Analog RGB for D-sub	Unsupport	support	support	support	Unsupport	support	support	support	support
15	* 0 IR 016\r	Source Digital RGB(DVI)	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	support	support
16	* 0 IR 017\r	Source PbPr for D-sub	Unsupport	support	support	support	Unsupport	support	support	support	support
17	* 0 IR 018\r	Source S-Video	Unsupport	support	support	support	Unsupport	support	support	support	support
18	* 0 IR 019\r	Source Composite Video	Unsupport	support	support	support	Unsupport	support	support	support	support
19	* 0 IR 020\r	Source Component Video	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	support	support	support	support
20	* 0 IR 021\r	Aspect ratio 16:9	Unsupport	support	support	support	Unsupport	support	support	support	support
21	* 0 IR 022\r	Aspect ratio 4:3	Unsupport	support	support	support	Unsupport	support	support	support	support

Model Name >>			X1170	X1270	X1276	P1373W	H6500	H5370BD	X1263	P1163 P1273 P1276 P1273B	P1373WB
22	* 0 IR 023\r	Volume +	Unsupport	support	support	support	Unsupport	support	support	support	support
23	* 0 IR 024\r	Volume –	Unsupport	support	support	support	Unsupport	support	support	support	support
24	* 0 IR 025\r	Brightness	Unsupport	support	support	support	Unsupport	support	support	support	support
25	* 0 IR 026\r	Contrast	Unsupport	support	support	support	Unsupport	support	support	support	support
26	* 0 IR 027\r	Color Temperature	Unsupport	support	support	support	Unsupport	support	support	support	support
27	* 0 IR 028\r	Source Analog RGB for DVI Port(DVI-A)	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
28	* 0 IR 029\r	Source Analog YPbPr for DVI Port	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
29	* 0 IR 030\r	Hide	Unsupport	support	support	support	Unsupport	support	support	support	support
30	* 0 IR 031\r	Source	Unsupport	support	support	support	Unsupport	support	support	support	support
31	* 0 IR 032\r	Video: Color saturation adjustment	Unsupport	support	support	support	Unsupport	support	support	support	support
32	* 0 IR 033\r	Video: Hue adjustment	Unsupport	support	support	support	Unsupport	support	support	support	support
33	* 0 IR 034\r	Video: Sharpness adjustment	Unsupport	support	support	support	Unsupport	support	support	support	support
34	* 0 IR 035\r	Query Model name	Unsupport	support	support	support	Unsupport	support	support	support	support
35	* 0 IR 036\r	Query Native display resolution	Unsupport	support	support	support	Unsupport	support	support	support	support
36	* 0 IR 037\r	Query company name	Unsupport	support	support	support	Unsupport	support	support	support	support
37	* 0 IR 040\r	Aspect ratioL.Box	Unsupport	Unsupport	Unsupport	support	Unsupport	support	Unsupport	Unsupport	support

Model Name >>			X1170	X1270	X1276	P1373W	H6500	H5370BD	X1263	P1163 P1273 P1276 P1273B	P1373WB
38	* 0 IR 041\r	Aspect ratio 1:1	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
39	* 0 IR 042\r	Keystone Up	Unsupport	support	support	support	Unsupport	support	support	support	support
40	* 0 IR 043\r	Keystone Down	Unsupport	support	support	support	Unsupport	support	support	support	support
41	* 0 IR 044\r	Keystone Left	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
42	* 0 IR 045\r	Keystone Right	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
43	* 0 IR 046\r	Zoom	Unsupport	support	support	support	Unsupport	support	support	support	support
44	* 0 IR 047\r	e-Key	Unsupport	support	support	support	Unsupport	support	support	support	support
45	* 0 IR 048\r	Color RGB	Unsupport	Unsupport	support	support	Unsupport	support	Unsupport	Unsupport	Unsupport
46	* 0 IR 049\r	Language	Unsupport	support	support	support	Unsupport	support	support	support	support
47	* 0 IR 050\r	Source HDMI	Unsupport	Unsupport	support	support	Unsupport	support	Unsupport	support	support
48	* 0 IR 051\r	ECO mode	Unsupport	support	support	support	Unsupport	support	support	support	support
49	* 0 IR 052\r	Query ECO mode	Unsupport	support	support	support	Unsupport	support	support	support	support
50	* 0 Lamp ?\r	Query the lamp ON/OFF	Unsupport	support	support	support	Unsupport	Unsupport	support	support	support
51	* 0 Lamp\r	Query the lamp hours	Unsupport	support	support	support	Unsupport	Unsupport	support	support	support
52	* 0 Src ?\r	Query source input type	Unsupport	support	support	support	Unsupport	Unsupport	support	support	support

Function command summary table:

Model Name >>			X113 P1383W P1283 H5380BD	S1283e S1283Hne S1383WHne	P7305 P7505 P7605	H9505BD	U5213 U5313W	K132 K135	K335	K137	C205
Supported baud rates		110	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		300	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		600	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		1200	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		2400	Unsupport	Unsupport	support	support	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		4800	Unsupport	Unsupport	support	support	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		9600	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
		14400	Unsupport	Unsupport	support	support	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		19200	Unsupport	Unsupport	support	support	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		38400	Unsupport	Unsupport	support	support	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		57600	Unsupport	Unsupport	support	support	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
		115200	Unsupport	Unsupport	support	support	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
No	Code (character)	Function feature									
1	OKOKOKOKOK\r	Power On	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
2	* 0 IR 001\r	Power On	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
3	* 0 IR 002\r	Power Off	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
4	* 0 IR 004\r	Keystone	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport

Model Name >>			X113 P1383W P1283 H5380BD	S1283e S1283Hne S1383WHne	P7305 P7505 P7605	H9505BD	U5213 U5313W	K132 K135	K335	K137	C205
5	* 0 IR 006\r	Mute	support(with Volume model only)	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
6	* 0 IR 007\r	Freeze	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
7	* 0 IR 008\r	Menu	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
8	* 0 IR 009\r	Up	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
9	* 0 IR 010\r	Down	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
10	* 0 IR 011\r	Right	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
11	* 0 IR 012\r	Left	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
12	* 0 IR 013\r	Enter	Unsupport	Unsupport	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
13	* 0 IR 014\r	Re-Sync	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
14	* 0 IR 015\r	Source Analog RGB for D-sub	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
15	* 0 IR 016\r	Source Digital RGB(DVI)	support	support	Unsupport	Unsupport	support	Unsupport	Unsupport	Unsupport	Unsupport
16	* 0 IR 017\r	Source PbPr for D-sub	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
17	* 0 IR 018\r	Source S-Video	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
18	* 0 IR 019\r	Source Composite Video	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
19	* 0 IR 020\r	Source Component Video	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
20	* 0 IR 021\r	Aspect ratio 16:9	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
21	* 0 IR 022\r	Aspect ratio 4:3	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport

Model Name >>			X113 P1383W P1283 H5380BD	S1283e S1283Hne S1383WHne	P7305 P7505 P7605	H9505BD	U5213 U5313W	K132 K135	K335	K137	C205
22	* 0 IR 023\r	Volume +	support(with Volume model only)	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
23	* 0 IR 024\r	Volume –	support(with Volume model only)	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
24	* 0 IR 025\r	Brightness	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
25	* 0 IR 026\r	Contrast	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
26	* 0 IR 027\r	Color Temperature	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
27	* 0 IR 028\r	Source Analog RGB for DVI Port(DVI-A)	support	support	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
28	* 0 IR 029\r	Source Analog YPbPr for DVI Port	support	support	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
29	* 0 IR 030\r	Hide	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
30	* 0 IR 031\r	Source	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
31	* 0 IR 032\r	Video: Color saturation adjustment	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
32	* 0 IR 033\r	Video: Hue adjustment	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
33	* 0 IR 034\r	Video: Sharpness adjustment	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
34	* 0 IR 035\r	Query Model name	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
35	* 0 IR 036\r	Query Native display resolution	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
36	* 0 IR 037\r	Query company name	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
37	* 0 IR 040\r	Aspect ratioL.Box	support(H5380BD Only)	Unsupport	support	support	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport

Model Name >>			X113 P1383W P1283 H5380BD	S1283e S1283Hne S1383WHne	P7305 P7505 P7605	H9505BD	U5213 U5313W	K132 K135	K335	K137	C205
38	* 0 IR 041\r	Aspect ratio 1:1	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
39	* 0 IR 042\r	Keystone Up	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
40	* 0 IR 043\r	Keystone Down	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
41	* 0 IR 044\r	Keystone Left	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
42	* 0 IR 045\r	Keystone Right	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
43	* 0 IR 046\r	Zoom	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
44	* 0 IR 047\r	e-Key	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
45	* 0 IR 048\r	Color RGB	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport	Unsupport
46	* 0 IR 049\r	Language	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
47	* 0 IR 050\r	Source HDMI	support(With HDMI Model Only)	support(With HDMI Model Only)	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
48	* 0 IR 051\r	ECO mode	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
49	* 0 IR 052\r	Query ECO mode	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
50	* 0 Lamp ?\r	Query the lamp ON/OFF	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
51	* 0 Lamp\r	Query the lamp hours	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport
52	* 0 Src ?\r	Query source input type	support	support	support	support	support	Unsupport	Unsupport	Unsupport	Unsupport

Function command summary table:

Model Name >>			P1510	H6520BD	X113H X113PH
Supported baud rates		110	Unsupport	Unsupport	Unsupport
		300	Unsupport	Unsupport	Unsupport
		600	Unsupport	Unsupport	Unsupport
		1200	Unsupport	Unsupport	Unsupport
		2400	support	Unsupport	Unsupport
		4800	support	Unsupport	Unsupport
		9600	support	Unsupport	Unsupport
		14400	support	Unsupport	Unsupport
		19200	support	Unsupport	Unsupport
		38400	support	Unsupport	Unsupport
		57600	support	Unsupport	Unsupport
		115200	support	Unsupport	Unsupport
No	**Code (character)**	**Function feature**			
1	OKOKOKOKOK\r	Power On	support	Unsupport	Unsupport
2	* 0 IR 001\r	Power On	support	Unsupport	Unsupport
3	* 0 IR 002\r	Power Off	support	Unsupport	Unsupport
4	* 0 IR 004\r	Keystone	support	Unsupport	Unsupport

Model Name >>			P1510	H6520BD	X113H X113PH
5	* 0 IR 006\r	Mute	support	Unsupport	Unsupport
6	* 0 IR 007\r	Freeze	support	Unsupport	Unsupport
7	* 0 IR 008\r	Menu	support	Unsupport	Unsupport
8	* 0 IR 009\r	Up	support	Unsupport	Unsupport
9	* 0 IR 010\r	Down	support	Unsupport	Unsupport
10	* 0 IR 011\r	Right	support	Unsupport	Unsupport
11	* 0 IR 012\r	Left	support	Unsupport	Unsupport
12	* 0 IR 013\r	Enter	Unsupport	Unsupport	Unsupport
13	* 0 IR 014\r	Re-Sync	support	Unsupport	Unsupport
14	* 0 IR 015\r	Source Analog RGB for D-sub	support	Unsupport	Unsupport
15	* 0 IR 016\r	Source Digital RGB(DVI)	Unsupport	Unsupport	Unsupport
16	* 0 IR 017\r	Source PbPr for D-sub	support	Unsupport	Unsupport
17	* 0 IR 018\r	Source S-Video	support	Unsupport	Unsupport
18	* 0 IR 019\r	Source Composite Video	support	Unsupport	Unsupport
19	* 0 IR 020\r	Source Component Video	Unsupport	Unsupport	Unsupport
20	* 0 IR 021\r	Aspect ratio 16:9	support	Unsupport	Unsupport
21	* 0 IR 022\r	Aspect ratio 4:3	support	Unsupport	Unsupport

Model Name >>			P1510	H6520BD	X113H X113PH
22	* 0 IR 023\r	Volume +	support	Unsupport	Unsupport
23	* 0 IR 024\r	Volume –	support	Unsupport	Unsupport
24	* 0 IR 025\r	Brightness	support	Unsupport	Unsupport
25	* 0 IR 026\r	Contrast	support	Unsupport	Unsupport
26	* 0 IR 027\r	Color Temperature	support	Unsupport	Unsupport
27	* 0 IR 028\r	Source Analog RGB for DVI Port(DVI-A)	Unsupport	Unsupport	Unsupport
28	* 0 IR 029\r	Source Analog YPbPr for DVI Port	Unsupport	Unsupport	Unsupport
29	* 0 IR 030\r	Hide	support	Unsupport	Unsupport
30	* 0 IR 031\r	Source	support	Unsupport	Unsupport
31	* 0 IR 032\r	Video: Color saturation adjustment	support	Unsupport	Unsupport
32	* 0 IR 033\r	Video: Hue adjustment	support	Unsupport	Unsupport
33	* 0 IR 034\r	Video: Sharpness adjustment	support	Unsupport	Unsupport
34	* 0 IR 035\r	Query Model name	support	Unsupport	Unsupport
35	* 0 IR 036\r	Query Native display resolution	support	Unsupport	Unsupport
36	* 0 IR 037\r	Query company name	support	Unsupport	Unsupport
37	* 0 IR 040\r	Aspect ratioL.Box	support	Unsupport	Unsupport

Model Name >>			P1510	H6520BD	X113H X113PH
38	* 0 IR 041\r	Aspect ratio 1:1	Unsupport	Unsupport	Unsupport
39	* 0 IR 042\r	Keystone Up	support	Unsupport	Unsupport
40	* 0 IR 043\r	Keystone Down	support	Unsupport	Unsupport
41	* 0 IR 044\r	Keystone Left	Unsupport	Unsupport	Unsupport
42	* 0 IR 045\r	Keystone Right	Unsupport	Unsupport	Unsupport
43	* 0 IR 046\r	Zoom	support	Unsupport	Unsupport
44	* 0 IR 047\r	e-Key	Unsupport	Unsupport	Unsupport
45	* 0 IR 048\r	Color RGB	Unsupport	Unsupport	Unsupport
46	* 0 IR 049\r	Language	support	Unsupport	Unsupport
47	* 0 IR 050\r	Source HDMI	support	Unsupport	Unsupport
48	* 0 IR 051\r	ECO mode	support	Unsupport	Unsupport
49	* 0 IR 052\r	Query ECO mode	support	Unsupport	Unsupport
50	* 0 Lamp ?\r	Query the lamp ON/OFF	support	Unsupport	Unsupport
51	* 0 Lamp\r	Query the lamp hours	support	Unsupport	Unsupport
52	* 0 Src ?\r	Query source input type	support	Unsupport	Unsupport